

# **Update Hints**

**K.M.E.**

**VL340 / VL350**



## **VL340 / VL350: Hints about Updating to Version 1.23 r41**

Since Version 1.23 the VL340 / VL350 supports Infrared USB Remote Control Receiver. Therefore you need an usual USB Hub, which must be connected to the USB Port of the VL340 / VL350. Then you could use the ports of the Hub for the connection of the receiver and the mass storage device.

The following remote controls are fully functional and tested successful with the VL340 / VL350:

- > HAMA MCE Remote Control
- > DELOCK Universal Remote Control

Basically, there are more Remote Controls and devices with USB-HID Receiver, which could be connected to the VL340 / VL350. But its not guaranteed, that those devices are supporting the whole functionality.

### **How to update the VL340 / VL350 firmware:**

- Copy the file VL3x0\_V1\_23.hex directly into the root of the USB mass storage device
- Connect the USB mass storage device to the VL340 / VL350 and power on the device
- If the USB LED flashes green, press the “Previous” and “Next” Button of the USB Player simultaneously till the USB LED flashes orange.
- Wait till the USB LED flashes green (ca. 10 seconds)
- The update is finished

**VL340 / VL350 Functionality (HAMA MCE Remote Control):**

